

## Arc Wash Mode A (8 Channel)

DMX Chanel	Function	Description	Value
1	LED Color	RED LED intensity	0-255
2	LED Color	Green LED intensity	0-255
3	LED Color	Blue LED intensity	0-255
4	Dimmer	Dimmer Segment 1	0-255
5	LED Color	RED LED intensity	0-255
6	LED Color	Green LED intensity	0-255
7	LED Color	Blue LED intensity	0-255
8	Dimmer	Dimmer Segment 2	0-255

## Arc Wash Mode P (6 Channel)

DMX Chanel	Function	Discription	Value
1	LED Color	Red LED intensity Segment 1	0-255
2	LED Color	Green LED Intensity Segment 1	0-255
3	LED Color	Blue LED Intensity Segment 1	0-255
4	LED Color	Red LED intensity Segment 2	0-255
5	LED Color	Green LED Intensity Segment 2	0-255
6	LED Color	Blue LED Intensity Segment 2	0-255

## Arc Wash Mode F (6 Channel)

DMX Chanel	Function	Discription	Value
1	Dimmer	Master Dimmer	0-152
2	LED Color	Red LED intensity	153-242
3	LED Color	Green LED Intensity	243-255
4	LED Color	Blue LED Intensity	0-255
5	Strobe	No Function	0-9
		Strobe (slow to fast)	10-57
		No Function	58-59
		Pulse On to Off (slow to fast)	60-108
		No Function	109-110
		Pulse Off to On (slow to fast)	111-159
		No Function	160-161
		Random Strobe	162-255
6	Macro	No Function	0-9
		Color Fade (slow to fast)	10-50
		Color Fade RGB (slow to fast)	51-91
		Color Fade Chase	92-132
		Color Snap	133-173
		Color Pulse	174-214
		Random Macro	215-255