

## Bright Stripe DMX Profile

### Mode 1 (3 Channels)

DMX Chanel	Function	Description	Value
1	LED Color	Red LED intensity	0-255
2	LED Color	Green LED Intensity	0-255
3	LED Color	Blue LED Intensity	0-255

### Mode 2 (24 Channels)

DMX Chanel	Function	Description	Value
1	LED Color	Red LED intensity	0-255
2	LED Color	Green LED Intensity	0-255
3	LED Color	Blue LED Intensity	0-255
" "	" "	" "	" "
22	LED Color	Red LED intensity	0-255
23	LED Color	Green LED Intensity	0-255
24	LED Color	Blue LED Intensity	0-255

### Mode 3 (48 Channels)

DMX Chanel	Function	Description	Value
1	LED Color	Red LED intensity	0-255
2	LED Color	Green LED Intensity	0-255
3	LED Color	Blue LED Intensity	0-255
" "	" "	" "	" "
46	LED Color	Red LED intensity	0-255
47	LED Color	Green LED Intensity	0-255
48	LED Color	Blue LED Intensity	0-255

# Mode 4 (6 Channels)

DMX Chanel	Function	Description	Value
1	LED Color	Red LED intensity	0-255
2	LED Color	Green LED Intensity	0-255
3	LED Color	Blue LED Intensity	0-255
4	Strobe	Strobe (slow to fast)	0-255
5	Macro	No Function	0-1
		Color fade (slow to fast)	2-19
		Color Snap (slow to fast)	20-39
		Color Scroll (slow to fast)	40-59
		Macro Effect 1	60-79
		Macro Effect 2	80-99
		Macro Effect 3	100-119
		Macro Effect 4	120-139
		Macro Effect 5	140-159
		Macro Effect 6	160-179
		Macro Effect 7	180-199
		Macro Effect 8	200-219
		Macro Effect 9	220-229
Macro Effect 10	230-249		
Macro Effect 11	250-255		
6	Dimmer	Dimmer Off to Full	0-255