

N-E Color Strip DMX Profile

DMX Channel	Function	Description	Value
1	Dimmer, Strobe Macros	Dimmer (Ch 2-13 dimmer valid)	0-10
		Strobe (Ch 2-13 dimmer valid)	11-51
		Color Fade (slow to fast)	52-83
		Color Snaps (slow to fast)	84-115
		Color Chase (red,purple-slow to fast)	116-123
		Color Chase (red,yellow-slow to fast)	124-139
		Color Chase (green,aqua-slow to fast)	140-147
		Color Chase (blue,purple-slow to fast)	148-155
		Color Chase (blue,aqua-slow to fast)	156-163
		Color Chase (purple,green-slow to fast)	164-179
		Color Chase (yellow,blue-slow to fast)	180-195
		Color Chase (aqua,red-slow to fast)	196-211
		Color Chase (slow to fast)	212-227
		Color Chase 2 (slow to fast)	228-243
		Color Chase 3 (slow to fast)	244-251
		Color Chase 4	252-255
2	LED Color	Red full bar	0-255
3	LED Color	Green full bar	0-255
4	LED Color	Blue full bar	0-255
5	LED Color	Red 1st segment	0-255
6	LED Color	Green 1st segment	0-255
7	LED Color	Blue 1st segment	0-255
8	LED Color	Red 2nd segment	0-255
9	LED Color	Green 2nd segment	0-255
10	LED Color	Blue 2nd segment	0-255
11	LED Color	Red 3rd segment	0-255
12	LED Color	Green 3rd segment	0-255
13	LED Color	Blue 3rd segment	0-255